

## T92010PT - 10w - 12v dc - IP67 Potted LED Power Supply

### Description

The T92010PT surface-mount 10w 12v weatherproof power supply.

To use in enclosure use code T92010ENC mounted into a black polycarbonate boxes, for mounting on a walls or post hidden behind planting and landscape features, under decking or in outbuildings, T9599 Stainless steel spikes are optional.



<b>Electrical data</b>	Constant voltage 10w 12v, input voltage of 240v. Non-dimmable. No load power consumption of less than 0.5w.
<b>Mechanical data</b>	40.5mm x 98mm x 27mm IP67
<b>Protection Functions</b>	Over Load- When connected load is over 120% of rated load, the product will shut down and enter protection status and will self-recover when fault is removed.

## Installation Instructions

for surface mounting: Using a slotted screwdriver, rotate each of the 4 quarter-turn corner fixings 90 degrees to the "0" position and remove the lid to reveal the fixing slots in each corner. Secure the transformer to a wall or post with 5mm screws in each corner, or attach to optional transformer mounting stakes. Install the transformer on a wall or post approx. 30cm above ground.